

# Technical Specification

**Product Code:** GCBR052WH

**Description:** 13A Double Pole Switched Fused Connection Unit With Neon & Optional Flex Outlet



Representative Image

## General Information

<b>Dimensions</b>	88mm (W) x 88mm (H) x 8mm (D)
<b>Dimensions With Gasket</b>	91mm (W) x 91mm (H) x 9mm (D)
<b>Plate Design &amp; Finish</b>	Georgian Rope Edge Polished Cast Brass
<b>Insert &amp; Gasket Colour</b>	White
<b>Materials</b>	Front Plate: Cast Brass Insert, Switch, Fuse Drawer & Housing: Urea Neon Lens: Polycarbonate Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel Gasket: Nylon
<b>Maximum Voltage</b>	250V~ 50Hz
<b>Load Rating</b>	13A
<b>Plate Fixing Centres</b>	60.3mm
<b>Terminal Size</b>	5mmø
<b>Terminal Torque</b>	2.5Nm
<b>Terminal Capacity</b>	4 x 2.5mm <sup>2</sup> or 2 x 4mm <sup>2</sup>
<b>Switched</b>	Yes
<b>Double Pole</b>	Yes
<b>Twin Earth Terminals</b>	Yes
<b>Neon Indicator</b>	Yes (Red)
<b>Fuse Fitted</b>	13A (BS 1362)
<b>Flex Outlet</b>	Yes (10mmø Through Front of the Plate)
<b>Ingress Protection</b>	IP20
<b>Back Box Depth</b>	25mm Minimum
<b>Operational Temperature</b>	-5°C to +40°C
<b>Warranty</b>	10 Years
<b>Standards</b>	BS 1363-4: 2016 +A1: 2018 BS 1362:1973

## Additional Information

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.